

SHIELD Remote Annunciator Panel

Accessory for SHIELD ERCES

MODEL NUMBER: F42-10R-100

The SHIELD Remote Annunciator Panel (RA) provides automatic supervisory signals for malfunctions of Nextivity SHIELD EXTEND or SHIELD SOLO ERCES. In addition to being NEMA 4 rated and complying with NFPA and IFC fire codes, the RA features PoE architecture for quick installation and alarm configuration. The RA also offers real-time component monitoring through the Nextivity WAVE Portal.

Features and benefits include:

- Supports automatic supervisory signals for malfunctions of SHIELD ERCES installations
- Provides real-time system status for SHIELD EXTEND or SHIELD SOLO
- Operational status report via Nextivity WAVE Portal
- Simple alarm set up using the Nextivity WAVE PRO app
- Intuitive interconnection with the fire alarm control panel
- Category cable architecture for ease of install with PoE
- Complies with IFC and NFPA fire codes
- NEMA 4 enclosure



SHIELD Remote Annunciator Panel (RA)



Specifications

	Width	Length	Height
Dimensions	4.5 in	9 in	9 in
Power	PoE		
Connectivity	RJ45		



(front view)



(bottom view)

Certifications

Listed to UL 2524

FCC part 15



Supported Alarms

Normal AC power	Loss of normal AC power
Battery Charger Fail	Low Battery Capacity @ 30% of Capacity
Donor antenna disconnection	Active RF emitting device malfunction
System component malfunction	Donor antenna malfunction

Product specifications are subject to change without prior notification